

Overview

- Wi-Fi 6 Dual Band 4x4 (2.4/5GHz)
- Uplink: 1 x 2.5Gb (RJ-45) with PoE-In
- LAN: 1 x 1Gb (RJ-45)
- PoE-In (802.3at) or DC Input: 48V



Manufacturer: EdgeCore

Specifications

Radios:

- Concurrent Dual Band 2.4 GHz, 5 GHz
- 4x4:4 UL and DL MU-MIMO supporting up to 2.9Gbps data rate

Interfaces:

- Uplink: 1 x 10/100/1000/2.5GBase-T Ethernet, Auto MDIX, RJ-45 with 802.3at PoE
- LAN: 1 x 10/100/1000/2.5GBase-T Ethernet, Auto MDIX, RJ-45
- Console: 1 x RJ-45 Port

Physical

- Dimensions (L x W x H): 17.71in x 9.05in x 2.75in (45 cm x 23 cm x 7 cm)
- Power options
 - DC Input: 48 VDC (DC terminal block)
 - PoE input: 802.3at compliant (PSE injector is not included in standard package)
- Weight: 4.63 lb (2.10 kg)
- LED Indicator: 1 x multi-color LED (Power, System, Uplink, LAN, 2.4G, 5G)

- Buttons: 1 x Restart / Reset
- Environmental Conditions
 - Operating Temperature: -20°C(-4°F) to 50°C(122°F)
 - Operating Humidity: 10% to 95% non-condensing
- Power Consumption: 25 W max
- Antenna
 - Type: Internal Omni directional antenna (2.4 GHz & 5 GHz)
 - Gain: 5 dBi (2.4 GHz), 6 dBi (5 GHz)
- Mounting options
 - Pole mount (standard bracket including hose clamp)
 - Wall mount (standard bracket)

Radio

- Standards 802.11ax (Wi-Fi 6) concurrent dual-band 2.4, 5 GHz
- Supported Data Rates
 - 802.11b: 1, 2, 5.5, 11 Mbps
 - 802.11a/g: 6, 9, 12, 18, 24, 36, 48, 54 Mbps
 - 802.11n: 6.5 –300 Mbps (20 / 40 MHz)
 - 802.11ac: 6.5 –1733 Mbps (20 / 40 / 80 MHz)
 - 802.11ax: 3.6 –574 Mbps (2.4 GHz, 20 / 40 MHz)
 - 802.11ax: 3.6 –2400 Mbps (5 GHz, 20 / 40 / 80 MHz)
- Radio Chains: 2 x 2(2.4GHz) and 4 x 4(5GHz)
- Spatial Streams: 2; MU-MIMO support for 2.4GHz and 4; MU-MIMO support for 5GHz
- Aggregate Conducted Transmit Power
 - 2.4 GHz: Up to 23dBm*3
 - 5 GHz: Up to 26dBm*3
- Regulatory domain specific: 2.4–2.4835 GHz (US, Canada, ETSI, Japan, TW) 5.15–5.25 GHz (lower band)
US/Canada, TW 5.725–5.825 GHz (upper band) US/Canada, TW Europe 5.15–5.25 GHz, 5.25–5.35, 5.47–5.725 GHz
Japan 5.15–5.25 GHz, 5.25–5.35, 5.47–5.73 GHz
- Channelization
 - 2.4 GHz: 20 / 40 MHz
 - 5 GHz: 20 / 40 / 80 MHz
- Frequency Range
 - 2.400 –2.483 GHz
 - 5.150 –5.850 GHz
- Operating Channels
 - 2.4 GHz: 1-11 (US), 1-13 (Europe)
 - 5 GHz*4 : 36-165 (US), 36-140 (Europe)

Regulatory Compliance

- Radio: EN300 328 V2.2.2 (2019-07) EN301 893 V2.1.1(2017-05) 47 CFR FCC Part 15.247 47 CFR FCC Part 15.407 IC RSS-247 Issue 2 and RSS-Gen Issue 5 NCC LP0002 Section 4.10.1 (2020-07-01) NCC LP0002 Section 5.7 (2020-07-01) MIC certification Rule, Article 2 Paragraph 1 Item 19 MIC certification Rule, Article 2 Paragraph 1 Item 19-3

- Emissions: EN 301 489-1 V2.1.1 (2017-02) EN 301 489-17 V3.1.1 (2017-02) EN 55032:2015 AS/NZS CISPR 32:2015, Class B 47 CFR FCC Rules and Regulations Part 15 Subpart B, Class B Digital Device ICES-003, Issue 7 Class B CNS 13438 terminal equipment design certification, Article 3, Article 4, Article 6, Article 9 and Article 34 regulation
- Safety: Low Voltage Directive IEC 62368-1:2014; and/or EN 62368-1:2014+A11:2017; and/or BS 62368-1:2014+A11:2017 CNS 14336-1 IEC/EN 62368-1, IEC/EN 60950-1
- Taiwan RoHS: CNS 15663

What's in the box

Package Content:

- OAP-103 access point
- Mounting bracket and 4 x M6 screws
- DC terminal plug
- 3 x Cable glands
- 2 x Steel-band clamps for pole mount (2.5 inch diameter max.)
- Screw kit—4 screws and 4 plugs
- QR code card

Interface overview

- 48 VDC power input or 802.3at PoE
- Restart/Reset button
 - A quick press restarts the system
 - Press and hold for 5 seconds resets to factory default
- Console port (RJ-45)
- LAN1 Port: 1 Gbps connections to LAN devices
 - Port LED: On (link), Blinking (traffic)
- Uplink (PoE) Port: 2.5 Gbps connections to 802.3at PoE
 - Port LED: On (link), Blinking (traffic)
- System LED Indicators
 - 2.4G: On (radio on), Blinking (traffic)
 - 5G: On (link), Blinking (traffic)
- Power/Cloud/Uplink Tri-Color LED
 - Yellow green: On (power OK), Blinking (boot up)
 - Blue: On (cloud managed)
 - Purple: Blinking (uplink activity in cloud managed mode)
 - Orange: Blinking (uplink activity in stand-alone mode)
- Kensington lock slot